

User Guide

Trademark Information

Medialon is a trademark of 7thSense Design Ltd. Product or company names that mentioned in 7thSense Design Ltd publications are tradenames or trademarks of their respective owners, and such trademarks may also be registered in their respective countries.

Copyright Information

All Rights Reserved. This document is copyrighted © by 7thSense Design Ltd and shall not be reproduced or copied without express written authorization from 7thSense Design Ltd.

The information in this document is subject to change without notice. 7thSense Design Ltd assumes no responsibility for errors, and/or omissions contained in this information.

Document Revision

Date	Document Software version edition		Revision details	Author/Editor	
October 2022 1		Showmaster Editor 2.7.3	New release	Nate Pease	

M764-1

Download the Calendar installer for Showmaster:

https://portal.7thsense.one/medialon-downloads/Calendar%20Installer%20For%20Showmaster.zip

Unzip the installer download.

Copy the Calendar licence file into the Installer folder.

If you have more than one Calendar licence, this process will need to be repeated. Only one licence can be added to each Showmaster firmware.

Remove the serial number from the name in the licence file, leaving only mxmMedialonCalendar.lic

Open Showmaster Editor.

Select File/Firmware Management / Add/Update a MxM/MRC:



Click the 3 ... dots on the top right of the window to select a firmware for the Calendar MxM:

2	Add/Update a MXM/MRC ->	Create Custom Firmware						-		
Firm	nware to update (MRTX file):									
							L	1		
Firm	nware version:									
Cus	stom Version Prefix:	Custom Revision:	Creator Info:							
MXN	Ms/MRCs to update:									
File	e Name				Version	Туре	Status			
Select a firmulate to un	undata									
Select a fiffiware to u	puate									
Firmware packages										
File			Version			Creator Info				^
Showmaster.Firmwa	are.2.7.3-BWN_A82B55E0-1.mrt	x2	2.7.3-CUS_A82B5	55E0-1						
Showmaster.Firmwa	are.2.7.3-CAL_514355E0-1.mrtx		2.7.3-CAL_51435	5E0-1		cal23030103				
Showmaster.Firmwa	are.2.7.3-CAL_90C355E0-1.mrb	<2	2.7.3-CAL_90C35	55E0-1						
Showmaster.Firmwa	are.2.7.3-CAL_95C355E0-1.mrb		2.7.3-CAL_95C35	55E0-1		23030103				
Showmaster.Firmwa	are.2.7.3-CAL_A54355E0-1.mrb	(2	2.7.3-CAL_A5435	55E0-1		c23020103				
Showmaster.Firmwa	are.2.7.3-CUS_259355E0-1.mrb		2.7.3-CUS_25935	55E0-1						
Showmaster.Firmwa	are.2.7.3-CUS_8A0B55E0-1.mrb	<2	2.7.3-CUS_8A0B	55E0-1						
Showmaster.Firmwa	are.2.7.3-CUS_90C355E0-1.mrb		2.7.3-CUS_90C35	55E0-1		calendar 22079	999			
Showmaster.Firmwa	are.2.7.3-CUS_A54355E0-1.mrb	<2	2.7.3-CUS_A5435	55E0-1		c23030103-2				
Showmaster.Firmwa	are.2.7.3-DEK_4B3B55E0-1.mrb		2.7.3-DEK_4B3B5	5E0-1						
Showmaster.Firmwa	are.2.7.3-MQT_19BB55E0-1.mrt	x2	2.7.3-MQT_19BB	55E0-1						
Showmaster.Firmwa	are.2.7.3-XXA_414355E0-1.mrtx		2.7.3-XXA_41435	i5E0-1		calendar				
Showmaster.Firmwa	are.2.7.3-XXX_50C355E0-1.mrtx		2.7.3-XXX_50C35	i5E0-1						
Showmaster Firmwi	are ? 7 3 1 Reta mrtv?		2 7 3 1 Beta							
Showmaster.Firmwa	are.2.7.3.mrtx2		2.7.3							_
<									>	
Add De	lete							Ok	Cancel	
									Caneci	

Select Custom Version Prefix: CAL (optional)

In **Creator Info**: enter Calendar_[Showmaster serial number] (this is optional, but highly recommended as each Medialon Calendar licence is tied to a Showmaster's serial number).

Firmware to update (MRTX file):	Add/Update a MXM/MRC -> Create Custom Firmware			120		\times
C:\ProgramData\Medialon\Showmaster2\Showmaster.Firmware.2.7.3.mtb2 Firmware version: 2.7.3 Custom Version Prefix: CAL Custom Revision: 1 Creator Info: Calendar_33030029 MXMs/MRCs to update: File Name Version Type Status Add. File Name Version Type Status Add. File Name Compared to the	Firmware to update (MRTX file):					
Firmware version: 2.7.3 Custom Version Prefix: CL Custom Revision: 1 Creator Info: Calendar_33030029 MXMs/MRCs to update: Add. File Name Version Type Status Add. mrcAdvantechADAM.mrc6 6.7.0 MRC Genuine Add. mrcAdvantechADAM.mrc6 6.7.0 MRC Genuine Add. mrcAdvantechADAM.mrc6 6.7.0 MRC Genuine Add. mrcAdvantechADAM.mrc6 6.7.0 MRC Genuine	C:\ProgramData\Medialon\Showmaster2\Showmaster.Firmware.2.7.3.mrtx2					
Custom Version Prefix: CAL Custom Revision: 1 Creator Info: Calendar_33030029	Firmware version: 2.7.3					
MXMs/MRCs to update: Version Type Status Add File Name 0.7.0 MRC Genuine Genuine Add mrcAdvantechADAM.mrc6 6.7.0 MRC Genuine Genuine <td>Custom Version Prefix: CAL Custom Revision: 1 Creator Info: Calendar_33030029</td> <td></td> <td></td> <td></td> <td></td> <td></td>	Custom Version Prefix: CAL Custom Revision: 1 Creator Info: Calendar_33030029					
MXMs/MRCs to update: File Name Version Type Status Add mrcAdvantechADAM.mrc6 Genuine mrcArtNetDMX.mrc6 Genuine mrcControlDeviceMaster.mrc6 G.7.0 MRC Genuine mrcSobalCache.mrc6 G.7.0 MRC Genuine MRTX Destination Folder: C:\ProgramData\Medialon\Sbowmaster2						
File Name Version Type Status Add mrcAdvantechADAM,mrc6 6.7.0 MRC Genuine Add mrcAdvantechADAM,mrc6 6.7.0 MRC Genuine Constraints Constants Constants	MXMs/MRCs to update:					
mrcAdvantechADAM,mrc6 6.7.0 MRC Genuine mrcAdvK.mrc6 6.7.0 MRC Genuine mrcArtNetDMX.mrc6 6.7.0 MRC Genuine mrcCohrolDeviceMaster.mrc6 6.7.0 MRC Genuine mrcSolvalZsNAPEthemetD0.mrc6 6.7.0 MRC Genuine mrcShowMasterDMX.mrc6 6.7.0 MRC Genuine mrcShowMasterI.E.mrc6 6.7.0 MRC Genuine mrcShowMasterSentI.E.mrc6 6.7.0 MRC Genuine mrcShowMasterSentI.E.mrc6 6.7.0 MRC Genuine	File Name	Version	Туре	Status	^	
mrcAMX.mrc6 6.7.0 MRC Genuine mrcArtNetDMX.mrc6 6.7.0 MRC Genuine mrcCohrolDeviceMaster.mrc6 6.7.0 MRC Genuine mrcCohrolDeviceMaster.mrc6 6.7.0 MRC Genuine mrcCohrolDeviceMaster.mrc6 6.7.0 MRC Genuine mrcCohrolDeviceMaster.mrc6 6.7.0 MRC Genuine mrcSobalCache.mrc6 6.7.0 MRC Genuine mrcSotalEvelSealINK.mrc6 6.7.0 MRC Genuine mrcShowMasterDMX.mrc6 6.7.0 MRC Genuine mrcShowMasterIIDI.mrc6 6.7.0 MRC Genuine mrcShowMasterIIII.mrc6 6.7.0 MRC Genuine mrcShowMasterTimecode.mrc6 6.7.0 MRC Genuine mrcShowMasterTimecode.mrc6 6.7.0 MRC Genuine mrcShowMasterStill.mrc6 6.7.0 MRC Ge	mrcAdvantechADAM.mrc6	6.7.0	MRC	Genuine		
mrcArtNetDMX.mrc6 6.7.0 MRC Genuine mrcComtrolDeviceMaster.mrc6 6.7.0 MRC Genuine mrcColbalCache.mrc6 6.7.0 MRC Genuine mrcOpto22SNAPEthemetIO.mrc6 6.7.0 MRC Genuine mrcSobalCache.mrc6 6.7.0 MRC Genuine mrcSANDMX.mrc6 6.7.0 MRC Genuine mrcSNowMasterDMX.mrc6 6.7.0 MRC Genuine mrcShowMasterDMX.mrc6 6.7.0 MRC Genuine mrcShowMasterDMX.mrc6 6.7.0 MRC Genuine mrcShowMasterDMX.mrc6 6.7.0 MRC Genuine mrcShowMasterPMIDI.mrc6 6.7.0 MRC Genuine mrcShowMasterVIDI.mrc6 6.7.0 MRC Genuine mrcShowmasterTimecode.mrc6 6.7.0 MRC Genuine	mrcAMX.mrc6	6.7.0	MRC	Genuine		
mrcControlDeviceMaster.mrc6 6.7.0 MRC Genuine mrcCMotaldonFlexQMoMdbusTCP.mrc6 6.7.0 MRC Genuine mrcOpto225NAPEthernetIO.mrc6 6.7.0 MRC Genuine mrcSAcNDMX.mrc6 6.7.0 MRC Genuine mrcSbowmasterDMX.mrc6 6.7.0 MRC Genuine mrcShowmasterDMX.mrc6 6.7.0 MRC Genuine mrcShowmasterDMX.mrc6 6.7.0 MRC Genuine mrcShowmasterDMX.mrc6 6.7.0 MRC Genuine mrcShowMasterID.mrc6 6.7.0 MRC Genuine	mrcArtNetDMX.mrc6	6.7.0	MRC	Genuine	- 14	
mrcGlobalCache.mrc6 6.7.0 MRC Genuine mrcGlobalCache.mrc6 6.7.0 MRC Genuine mrcAddialonFlextOModbusTCP.mrc6 6.7.0 MRC Genuine mrcSACNDMX.mrc6 6.7.0 MRC Genuine mrcSactevelSeaLINK.mrc6 6.7.0 MRC Genuine mrcShowMasterIO.mrc6 6.7.0 MRC Genuine mrcShowMasterID.mrc6 6.7.0 MRC Genuine mrcShowMasterII.mrc6 6.7.0 MRC Genuine mrcShowMasterII.mrc6 6.7.0 MRC Genuine mrcShowMasterSerial.mrc6 6.7.0 MRC Genuine mrcShowMasterSerial.mrc6 6.7.0 MRC Genuine mrcShowMasterSiterII.mrc6 6.7.0 MRC Genuine	mrcComtrolDeviceMaster.mrc6	6.7.0	MRC	Genuine		
mrcMedialonFlexIOModbusTOP.mrc6 6.7.0 MRC Genuine mrcsAcXDNMX.mrc6 6.7.0 MRC Genuine mrcsAckevelSeaLINK.mrc6 6.7.0 MRC Genuine mrcsNowmasterDMX.mrc6 6.7.0 MRC Genuine mrcsNowMasterVIDI.mrc6 6.7.0 MRC Genuine mrcShowMasterVIDI.mrc6 6.7.0 MRC Genuine mrcShowMasterVIDI.mrc6 6.7.1 MRC Genuine mrcShowMasterVIDI.mrc6 6.7.0 MRC Genuine <td>mrcGlobalCache.mrc6</td> <td>6.7.0</td> <td>MRC</td> <td>Genuine</td> <td></td> <td></td>	mrcGlobalCache.mrc6	6.7.0	MRC	Genuine		
mrcsAbOMPEthemetiD.mrc6 6.7.0 MRC Genuine mrcsAbOMPEthemetiD.mrc6 6.7.0 MRC Genuine mrcSaeLevelSeaLINK.mrc6 6.7.0 MRC Genuine mrcShowmasterDMX.mrc6 6.7.0 MRC Genuine mrcShowmasterID.mrc6 6.7.0 MRC Genuine mrcShowmasterIDI.mrc6 6.7.0 MRC Genuine mrcShowmasterIDI.mrc6 6.7.0 MRC Genuine mrcShowmasterIID.mrc6 6.7.0 MRC Genuine	mrcMedialonFlexIOModbusTCP.mrc6	6.7.0	MRC	Genuine		
mrcSACNDMX.mrc6 6.7.0 MRC Genuine mrcSAcLevelSeaLINK.mrc6 6.7.0 MRC Genuine mrcShowmasterDMX.mrc6 6.7.0 MRC Genuine mrcShowMasterID.mrc6 6.7.1 MRC Genuine mrcShowMasterIDI.mrc6 6.7.0 MRC Genuine mrcShowMasterSerial.mrc6 6.7.0 MRC Genuine mrcShowmasterTimecode.mrc6 6.7.0 MRC Genuine mrcShowmasterTimecode.mrc6 6.7.0 MRC Genuine mrcShowmasterXSmrc6 6.7.0 MRC Genuine mrcShowmasterTimecode.mrc6 6.7.0 MRC Genuine mrcShowmasterTimecode.mrc6 6.7.0 MRC Genuine mrcShowmasterTimecode.mrc6 6.7.0 MRC Genuine mrcShowmasterTimecode.mrc6 6.7.0 MRC Genuine mrcShowmasterZ	mrcOpto22SNAPEthernetIO.mrc6	6.7.0	MRC	Genuine		
mrcSbauwmaster/DX,mrc6 6.7.0 MRC Genuine mrcShowmaster/DX,mrc6 6.7.0 MRC Genuine mrcShowmaster/DX,mrc6 6.7.0 MRC Genuine mrcShowMaster/IL:mrc6 6.7.0 MRC Genuine mrcShowMaster/IL:mrc6 6.7.0 MRC Genuine mrcShowMaster/IL:mrc6 6.7.0 MRC Genuine mrcShowMaster/Stall.mrc6 6.7.0 MRC Genuine mrcShowmaster/II:mecode.mrc6 6.7.0 MRC Genuine mrcShowmaster/XSmrc6 6.7.0 MRC Genuine MRTX Destination Folder: X X X	mrcsACNDMX.mrc6	6.7.0	MRC	Genuine		
mrcShowMasterOMX.mrc6 6.7.0 MRC Genuine mrcShowMasterIDMX.mrc6 6.7.0 MRC Genuine mrcShowMasterIE.mrc6 6.7.0 MRC Genuine mrcShowMasterYIDI.mrc6 6.7.0 MRC Genuine mrcShowMasterStella.mrc6 6.7.0 MRC Genuine mrcShowMasterStella.mrc6 6.7.0 MRC Genuine mrcShowmasterTimecode.mrc6 6.7.0 MRC Genuine mrcShowmasterVS.mrc6 6.7.0 MRC Genuine MRTX Destination Folder: State St	mrcsealevelseaLINK.mrco	6.7.0	MRC	Genuine		
Initial control 0.7.0 MRC Genuine mrcShowMasterEmrc6 6.7.0 MRC Genuine mrcShowMasterSerial.mrc6 6.7.0 MRC Genuine mrcShowMasterTimecode.mrc6 6.7.0 MRC Genuine mrcShowmasterExtraction 6.7.0 MRC Genuine	mrcShowMasterDMX.mrcb	6.7.0	MRC	Genuine		
Initication/master/Linitod 0.7.1 MRC Genuine mrcShowMaster/DILmrc6 6.7.0 MRC Genuine mrcShowMaster/Timecode.mrc6 6.7.0 MRC Genuine mrcShowmaster/XSmrc6 6.7.0 MRC Genuine wrcShowmaster/XSmrc6 6.7.0 MRC Genuine MRTX Destination Folder:	micShowmasterLE mic6	6.7.1	MPC	Genuine		
Micclowinduction for the finite 6.7.0 MRC Genuine mrcShowMasterSerial.mrc6 6.7.0 MRC Genuine mrcShowmasterTimecode.mrc6 6.7.0 MRC Genuine mrcShowmasterXSmrc6 6.7.0 MRC Genuine MRTX Destination Folder: Image: CityProgramData\Medialon\Showmaster2 Image: CityProgramData\Medialon\Showmaster2	mrcShowMasterMIDI mrc6	670	MRC	Genuine		
micds/micds/minds/micds/m	mrcshowMasterSerial mrc6	670	MRC	Genuine		
MRTX Destination Folder:	mrcShowmasterTimecode.mrc6	6.7.0	MRC	Genuine		
MRTX Destination Folder: C:\ProgramData\Medialon\Showmaster2	mrcShowmasterXS mrc6	670	MRC	Genuine	~	
MRTX Destination Folder: C:\ProgramData\Medialon\Showmaster2	<			>		
MRTX Destination Folder: C:\ProgramData\Medialon\Showmaster2						
C:\ProgramData\Medialon\Showmaster2	MRTX Destination Folder:					
	C:\ProgramData\Medialon\Showmaster2					
Update Cancel						

Click **Add**, navigate to the installer folder and then Open.

« Licenses > Calendar Licensing	CalendarMxMDownload	~	Ū	2)	Searc	h Calen	darM	IxMDo	wnlo.
w folder							•	•		?
↑ Name	^ MedialonCalendar mis6									
			٢	lo pre	vie	w avai	ilable.			
~ <	>									
File name: mxmMedialonCalendar.n	nis6		~	Me	dia C	lon M)pen	Iodule I	nstal	ler (*.m Cancel	ni ~

Click **Update** to begin the installation. Once the installation is complete you should see this message. Click **OK**:

Create Custom Firmware								
The custom firmware version '2.7.3-CUS_B1D355E0-1' has been successfully o 'C\ProgramData\Medialon\Showmaster2\Showmaster.Firmware.2.7.3-CUS_B1D	preated in file: 355E0-1.mrtx2'.							
	<u>Ok</u>							

Click **OK** when asked to install the firmware:



Once the firmware is installed in Showmaster Editor, connect to the Showmaster, then select **Firmware Info & Update**:

edialon Showmaster Editor 2.7.2

dit	Showmaster	Object	Windows	Help						
a	Connect		Ctrl+Alt+K	rkspe						
'0WS	Disconn	Disconnect Sh								
ect	Configu	Configuration								
)evici aske	Send Pro	Send Project								
'anel	Retrieve Project									
lser` Xue L	Manage	Logs								
lser (Firmwar	e Info &	Update _K							
leso	Reboot		3							
	Shutdov	/n								

Click Update and use the password 'medialon' to install the custom firmware on the Showmaster.

Firmv	Firmware Info & Update							
Editor Firmware Version: 2.7.3-CUS_B1D355E0-2								
S	howma	ster Firmware Version: 2.7.2						
Grour	ე	Name	Showmaster Version	Editor Version				
	- App	borindmm.dll	14.0.3593.25826	14.0.3593.25826	A			
	Арр	cc32100mt.dll	10.0.0.0	10.0.0.0				
	Арр	COLXT70.bpl	1.0.7.0	1.0.7.0				
	Арр	Data\SSL	[Not Present]	1.0.1.0				
	Арр	IndyCore140.bpl	14.0.3593.25826	14.0.3593.25826				
	Арр	IndyProtocols140.bpl	14.0.3593.25826	14.0.3593.25826				
	Арр	IndySystem140.bpl	14.0.3593.25826	14.0.3593.25826				
	Арр	libeay32.dll	1.0.2q	1.0.2q				
	Арр	libmySQL.dll	8.7.5.5	8.7.5.5				
	Арр	MedialonManagerRT.cfg-dist	2.0.1	2.0.1				
	Арр	MedialonManagerRT.exe	2.7.2.0	2.7.3.0				
	Арр	MedialonTimecodeReader.exe	6.1.0.0	6.1.0.0				
	Арр	mHTTPServerLib.dll	1.0.7.0	1.0.7.0				
	Арр	mLogDB.cfg-dist	2.0.0	2.0.0				
	Арр	mMECCommunicationHub.cfg-dist	2.0.0	2.0.0				
	Арр	mMECCommunicationHub.exe	6.0.0.0	6.0.0.0				
	Арр	mmwdc6.dll	6.1.0.0	6.1.0.0				
	Арр	mNDDLib.dll	1.0.3.0	1.0.3.0				
	Арр	modsE.dll	4.1.0.0	4.1.0.0				
	Арр	modsEngine.exe	4.1.2.0	4.1.2.0				
	Арр	mOpenCAPHTTPServerSrvCore.cfg-dist	2.0.0	2.0.0				
	Арр	mOpenCAPHTTPServerSrvCore.exe	1.1.1.0	1.2.1.0				
	A n n	MORANCARIA/CCARios afa diat						
	Save	Сору			Update Cancel			

Click **OK** and wait for the Showmaster to reboot automatically. Once the reboot is complete, connect to the Showmaster and create a Calendar device.



E: info@7thsense.one W: 7thsense.one

7thSense Design Ltd

2 The Courtyard Shoreham Road Upper Beeding Steyning West Sussex BN44 3TN UK

T: +44 (0) 1903 812299

7thSense LLC, Michigan

332 E Lincoln Ave Suite 100 Royal Oak, MI 48067 USA

T: +1 248 599 2717

7thSense LLC, Orlando

4207 Vineland Rd Suite M1 Orlando, FL 32811 USA

T: +1 407 505 5200